

## **SECTION 26 05 20 CONDUCTORS AND CABLES**

### **PART 1 – GENERAL**

#### **1.1 RELATED DOCUMENTS**

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions apply to this Section.

#### **1.2 SUMMARY**

- A. This Section includes building wires and cables and associated connectors, splices, and terminations for wiring systems rated 600 V and less.

#### **1.3 SUBMITTALS**

- A. Field Test Reports: Indicate and interpret test results for compliance with performance requirements.

#### **1.4 QUALITY ASSURANCE**

- A. Testing Agency Qualifications: In addition to requirements specified in Division 1 Section "Quality Control," an independent testing agency shall meet OSHA criteria for accreditation of testing laboratories, Title 29, Part 1907; or shall be a full-member company of the InterNational Electrical Testing Association.
  - 1. Testing Agency's Field Supervisor: Person currently certified by the InterNational Electrical Testing Association or the National Institute for Certification in Engineering Technologies, to supervise on-site testing.
- B. Listing and Labeling: Provide wires and cables specified in this Section that are listed and labeled.
  - 1. The terms "Listed" and "Labeled": As defined in NFPA 70, Article 100
  - 2. Listing and Labeling Agency Qualifications: "A nationally recognized testing laboratory" as defined in OSHA Regulation 1910.7
- C. Comply with NFPA 70.

#### **1.5 DELIVERY, STORAGE, AND HANDLING**

- A. Deliver wires and cables according to NEMA WC 26.

#### **1.6 COORDINATION**

- A. Coordinate layout and installation of cables with other installations.
- B. Revise locations and elevations from those indicated, as required to suit field conditions and as approved by Architect.

## 2.0 PRODUCTS

### 2.1 MANUFACTURERS

- A. Available Manufacturers: Subject to compliance with requirements, manufacturers offering products that may be incorporated into the Work include, but are not limited to, the following:
- B. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
  - 1. Wires and Cables:
    - a. Alcan Aluminum Corporation; Alcan Cable Division
    - b. American Insulated Wire Corporation; Leviton Manufacturing Company
    - c. BICC Brand-Rex Company
    - d. Carol Cable Company, Inc.
    - e. Senator Wire and Cable Company
    - f. Southwire Company
  - 2. Connectors for Wires and Cables:
    - a. AMP Incorporated.
    - b. General Signal; O-Z/Gedney Unit.
    - c. Monogram Co.; AFC.
    - d. Square D Co.; Anderson.
    - e. 3M Company; Electrical Products Division.

### 2.2 BUILDING WIRES AND CABLES

- A. UL-listed building wires and cables with conductor material, insulation type, cable construction, and rating as specified "Wire and Insulation Applications" Article.
- B. Rubber Insulation Material: Comply with NEMA WC 3.
- C. Thermoplastic Insulation Material: Comply with NEMA WC 5.
- D. Cross-Linked Polyethylene Insulation Material: Comply with NEMA WC 7.
- E. Ethylene Propylene Rubber Insulation Material: Comply with NEMA WC 8.
- G. Conductor Material: Copper.
- H. Stranding: Solid conductor for No. 10 AWG and smaller; stranded conductor for larger than No. 10 AWG.

### 2.3 CONNECTORS AND SPLICES

- A. UL-listed, factory-fabricated wiring connectors of size, ampacity rating, material, type, and class for application and service indicated. Comply with Project's installation requirements and as specified "Wire and Insulation Applications" Article.

## PART 3 - EXECUTION

### 3.1 EXAMINATION

- A. Examine raceways and building finishes to receive wires and cables for compliance with requirements for installation tolerances and other conditions affecting performance of wires and cables. Do not proceed with installation until unsatisfactory conditions have been corrected.

### 3.2 WIRE AND INSULATION APPLICATIONS

- A. Feeders and branch circuits: Type THHN/THWN, in raceway.

### 3.3 INSTALLATION

- A. Install wires and cables as indicated, according to manufacturer's written instructions and NECA's "Standard of Installation."
- B. Pull Conductors: Use manufacturer-approved pulling compound or lubricant where necessary; compound used must not deteriorate conductor or insulation. Do not exceed manufacturer's recommended maximum pulling tensions and sidewall pressure values.
- C. Use pulling means, including fish tape, cable, rope, and basket-weave wire/cable grips, that will not damage cables or raceway.
- D. Install exposed cables, parallel and perpendicular to surfaces of exposed structural members, and follow surface contours where possible.
- F. Support cables according to Division 26 Section "Basic Electrical Materials and Methods."
- E. Seal around cables penetrating fire-rated elements.
- F. Identify wires and cables according to Division 26 Section "Basic Electrical Materials and Methods."
- H. Identify wires and cables according to Division 26 Section "Electrical Identification."

### 3.4 CONNECTIONS

- A. Conductor Splices: Keep to minimum.
- B. Install splices and tapes that possess equivalent or better mechanical strength and insulation ratings than conductors being spliced.
- C. Use splice and tap connectors compatible with conductor material.
- D. Wiring at Outlets: Install conductor at each outlet, with at least 12 inches of slack.

- E. Connect outlets and components to wiring and to ground as indicated and instructed by manufacturer.
- F. Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. If manufacturer's torque values are not indicated, use those specified in UL 486A and UL 486B.

### 3.5 FIELD QUALITY CONTROL

- A. Testing Agency: Owner will engage a qualified independent testing agency to perform field quality-control testing.
- B. Testing Agency: Engage a qualified independent testing agency to perform field quality-control testing.
- C. Testing: On installation of wires and cables and before electrical circuitry has been energized, demonstrate product capability and compliance with requirements.
  - 1. Procedures: Perform each visual and mechanical inspection and electrical test stated in NETA ATS, Section 7.3.1. Certify compliance with test parameters.
- D. Correct malfunctioning conductors and cables at Project site, where possible, and retest to demonstrate compliance; otherwise, remove and replace with new units and retest.

END OF SECTION 260520